

Altus Motor Quick Start Guide

Your shade has been shipped with the channels and the limits already set at the factory. Use this guide only if you need to change the factory setting. For more advanced settings, see the Somfy Altus RTS Motor Quick Reference Guide and Altus RTS Motor Programming and Limit Setting Instructions.



To reset limits

Important: To change a limit you must start by moving the shade to the existing limit.

- 1 Operate the shade to move it to the limit you want to change.
- 2 Press and hold the **Up** and **Down** buttons simultaneously until the shade jogs.
The shade operation changes to momentary and the limit is erased.
- 3 Operate the shade to move it to the correct limit.
- 4 Press and hold **Stop** until the shade jogs.

Changing Channels on Multiple Shades

Important: Changing channels on multiple shade can only be done one shade at a time. **Disconnect power from all shades except the one you are programming.**

The system has five channels indicated by the lights in the lower part of the remote. When the fifth channel is active, all lights are lit. You can program a channel to operate one shade or a group of shades.

The programming button on the back of the remote works as a toggle to turn the channels on and off. Program each shade separately by turning on the channel or channels you want active and turning off any currently active channels you do not want active.

To turn on a channel

- 1 Disconnect power from all shades except the one you are programming.
- 2 Press the **Channel** button and test the channels to find one that currently operates the shade.
- 3 Press the **Programming** button on the back of the remote to open programming.
- 4 Press the **Channel** button until the channel you want to turn on is lit.
- 5 Press the **Programming** button on the back of the remote to close programming.

To turn off a channel

- 1 Disconnect power from all shades except the one you are programming.
- 2 Press the **Channel** button to select an active channel that will continue to operate the shade.
- 3 Press the **Programming** button on the back of the remote to open programming.
- 4 Press the **Channel** button until the channel you want to turn off is lit.
- 5 Press the **Programming** button on the back of the remote to close programming.